© Illumino Ignis Ltd. 2026. All Rights Reserved

Illumino Ignis Ltd™
LIGHTING & FIRE DESIGN, SUPPLY & SUPPORT

CFP Relay Output Card (Reset, Fault, Aux. & Remote Relay Outputs)


Conventional - Panel

Part No. CFP762

www.illuminoignis.co.uk

Product Details

An optional system expansion device for use with CFP Standard 2-8 Zone Fire Panels or CFP AlarmSense 2-8 Zone Fire Panels.



Key Features

- An optional system expansion device for use with CFP Standard 2-8 Zone Fire Panels or CFP AlarmSense 2-8 Zone Fire Panels.
- Provides four panel-controlled volt free relay outputs (reset, fault, aux. fire and remote).
- PCB mounts inside the CFP fire panel.
- Reset relay is active during the panel's reset cycle.
- Fault relay is active in any fault condition. This relay is failsafe and normally energised - if power is removed from the panel the relay will changeover to produce a fault signal.
- Aux. fire relay is active in an alarm condition provided all relevant delays have expired.
- Remote relay is active during any Alarm Condition provided all relevant delays have expired.
- Outputs are NOT designed to switch mains voltages.

Technical Specifications

Product dimensions (mm)	82 W x 125 H x D 23mm
Weight	64g
Properties	Single pole changeover contacts; Rated at 1A 50V; 50V Isolation between relays, contacts and CFP & relays; 27mA active relay coil current @ 27.6V supply.

0203 00 44 855
sales@illuminoignis.co.uk
illuminoignis.co.uk

Illumino Ignis Ltd, Ignis House,
Imperial Way, Eagle Business Park,
Yaxley, Cambridgeshire, PE7 3GP