© Illumino Ignis Ltd. 2026. All Rights Reserved

Illumino Ignis Ltd™
LIGHTING & FIRE DESIGN, SUPPLY & SUPPORT


CFP Relay Output Card (8 Output Per Zone Relays)

Conventional - Panel

Part No. CFP764

www.illuminoignis.co.uk

Product Details



The C-TEC CFP764 Zone Relay Card is an optional expansion module designed for use with C-TEC CFP conventional fire alarm control panels.

Installed within the control panel, this relay card provides eight zone-specific relay outputs, allowing external equipment to be triggered when a corresponding fire alarm zone enters an alarm condition.

Each relay operates as a single pole changeover contact, enabling the fire alarm panel to interface with other systems such as building management systems, auxiliary signalling devices or additional control equipment.

The CFP764 is designed for use with CFP708-4 Standard 8 Zone Fire Panels and CFP708-2 AlarmSense 8 Zone Fire Panels, offering a simple way to expand system functionality and improve integration with other building services.

Key Features

- An optional system expansion device for use with CFP708-4 Standard 8 Zone Fire Panels or CFP708-2 AlarmSense 8 Zone Fire Panels.
- Provides eight output per zone relays which will changeover when the corresponding zone is in alarm (subject to certain conditions - for full details refer to the instructions, downloadable below).
- PCB mounts inside the CFP fire panel.
- Outputs are NOT designed to switch mains voltages.

Technical Specifications

Product dimensions (mm)	82 W x 125 H x D 23mm
Weight	90g.
Properties	Single pole changeover contacts; Rated at 1A 50V; 50V Isolation between relays, contacts and CFP & relays; 27mA active relay coil current @ 27.6V supply.

0203 00 44 855
sales@illuminoignis.co.uk
illuminoignis.co.uk

Illumino Ignis Ltd, Ignis House,
Imperial Way, Eagle Business Park,
Yaxley, Cambridgeshire, PE7 3GP