


Illumino Ignis Ltd

LIGHTING & FIRE DESIGN, SUPPLY & SUPPORT

Hochiki Address Programmer

Accessories – Test Equipment

Part No. TCH-B200

www.illuminoignis.co.uk

Product Details

Model TCH-B200 is a hand held address programmer designed to address the ESP range of Sensors and all other addressable devices such as wall sounders, mini modules and manual call points (with the use of a programming lead – sold separately)

The unit is designed to be light, robust and easy to use and operates from a single PP3 size battery, which gives the capacity for up to 8000 operations. The programmer is also capable of displaying the sensor analogue values.

Key Features

- Lightweight design
- Quick and reliable addressing
- Over 8000 address settings from one battery
- Displays sensor analogue value
- Ability to disable polling of sensors.



Technical Specifications

Battery Type	9 VDC
Operating Temperature Range	-10 °C to +50 °C
Colour / Case Material	White / ABS
Weight (g)	140 (Including Battery)
Dimensions(mm)	L160 x D30 x W99.5



Shown with ALN-EN sensor fitted
– not supplied