© Illumino Ignis Ltd. 2026. All Rights Reserved

Illumino Ignis Ltd™
LIGHTING & FIRE DESIGN, SUPPLY & SUPPORT

SmartCell Wireless Remote Indicator (Fire Detection Indicator Text)

Radio - Devices

Part No. SC-62-0211-0001-99

www.illuminoignis.co.uk

Product Details

The SmartCell wireless remote indicator is quick and easy to install and offers individual addressing at the SmartCell control panel.

Features include red fire indication LED, bidirectional 868 MHz communication and an anti-tamper locking mechanism.

This device is third party certified and compatible with the full SmartCell product range.



Key Features

- Fully wireless
- Quick and easy to install
- Red fire indication LED
- Unique design
- Inbuilt locking mechanism

Technical Specifications

General	Wireless frequency	868 MHz
Electrical	Power supply type	Batteries
	Batteries	3 x ER14505M 3.6 V lithium thionyl chloride batteries (Fanso or Titus)
	Power consumption	1.46 W max.
	Operating voltage	2.7 to 3.65 VDC
	Current consumption	0.1 to 400 mA
Physical	Physical dimensions	110 x 39 mm (Ø x D)
	Colour	White
	Mounting type	Wall mount
	Mounting base	Wireless
Environmental	Vandal proof	Yes
	Operating temperature	-10 to +55 °C
	Storage temperature	-10 to +30 °C (with batteries)
	Relative humidity	0 to 95% noncondensing
	Environment	Indoor
	IP rating	IP21C
Regulatory	Compliancy	CE
	Certification	CPR
	Standards	EN54-13 EN54-25

0203 00 44 855
sales@illuminoignis.co.uk
illuminoignis.co.uk

Illumino Ignis Ltd, Ignis House,
Imperial Way, Eagle Business Park,
Yaxley, Cambridgeshire, PE7 3GP